Checking Your Blood Glucose Using

TRUE METRIX GO

A guide for testing your blood glucose

Simple Steps to Test Your **Blood Glucose**

Meter, Test Strips & System Components



*Trying to recharge the battery or power the meter by plugging into an adaptor or an electrical outlet may cause meter to catch on fire and/or battery may explode. **USB Port For Data Download Only DO NOT use to charge battery or meter.

Blood Glucose Testing



Wash your hands with warm, soapy water.



With Test Strip still in Meter, touch Sample Tip to top of blood drop and allow blood to be drawn into Test Strip. Remove from blood drop immediately after dashes appear across Meter Display.



Remove Test Strip from vial and close vial immediately. Insert Test Strip into Test Port with Contact End (blocks facing up). The Meter turns on.



In as fast as 4 seconds, glucose result will be displayed. Discard Test Strip in the appropriate container.



Lance your finger. For single patient use only.



Changing Battery



Turn Meter over until the Meter label is facing up. Look for Battery Tray symbol $\overline{}$ on Meter label and pull Battery Tray out until battery is exposed. Replace battery.

*Meter uses CR2032 non-rechargeable battery

This guide provides a brief overview on testing your blood glucose. If you need information about setting up your Meter with correct date and time, consult the "Getting Started" section of System Instructions for Use. For more detailed information on complete blood glucose testing procedure, consult "Testing Blood" section in the System Instructions for Use. WARNING! Upon opening the test strip carton, examine the product for missing, damaged or broken parts. Ensure the test strip vial cap is securely closed. If the product is damaged or the vial cap is not closed, DO NOT use the test strips for testing; product may give inaccurate results.

